

BBxxx: 5" Boot Kits



Features:

- One-piece design for easy installation and superior water-sealing properties
- Kits include rubber BOOT, one Cushion Insert, and two Stainless Steel Hose Clamps
- For use with our 5" Entry Panels
- Additional configurations can be made using Barrel Cushions with appropriate mating hanger size
- Blank boots can be used to seal unused ports or can be field cut for custom hole configurations
- For rooftop entries use SCS30 Rubber Sealer

Construction:

- Boot jacket and Cushion Insert are manufactured from EPDM rubber; material meets ASTM-D2000 and SAE J200
- Hose clamps have 201 Stainless Steel band and housing with 305 Stainless Steel screw

Related Products:

- 5" Entry Panels, Cushion Inserts, Cushion Plugs, Barrel Cushions

BBxxx: 5" Boot Kits

Coax Cables

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
BB14F	1/4" Flex Coax	0.295"	1	Each
BB143F	1/4" Flex Coax	0.295"	3	Each
BB38	3/8" Coax	0.440"	1	Each
BB384	3/8" Coax	0.440"	4	Each
BB123AIR	1/2" Air Coax	0.580"	3	Each
BB12FLX	1/2" Flex Coax	0.520"	1	Each
BB123FLX	1/2" Flex Coax	0.520"	3	Each
BB124FLX	1/2" Flex Coax	0.520"	4	Each
BB12	1/2" Foam Coax	0.630"	1	Each
BB122	1/2" Foam Coax	0.630"	2	Each
BB123	1/2" Foam Coax	0.630"	3	Each
BB124	1/2" Foam Coax	0.630"	4	Each
BB129	1/2" Foam Coax	0.630"	9	Each
BBLR94	5/8" Coax	0.870"	4	Each
BB78	7/8" Coax	1.110"	1	Each
BB782	7/8" Coax	1.110"	2	Each
BB783	7/8" Coax	1.110"	3	Each
BB784	7/8" Coax	1.110"	4	Each
BB114	1-1/4" Coax	1.560"	1	Each
BB158	1-5/8" Coax	2.000"	1	Each
BB214	2-1/4" Coax	2.375"	1	Each
BBZERO	Blank, No Holes	N/A	0	Each

Mixed Coax

Part #	Cable Size & Type	Hole Sizes	# of Holes	U of M
BB121M	(1) 1/2" Foam Coax & (2) 7/8" Coax	0.63", 1.11"	3	Each
BB122M	(2) 1/2" Foam Coax & (1) 7/8" Coax	0.63", 1.11"	3	Each
BB123M	(3) 1/2" Foam Coax & (2) 7/8" Coax	0.63", 1.11"	5	Each
BB158M	(1) 1/2" foam Coax & (1) 1-5/8" Coax	0.63", 2.0"	2	Each

BBxxx: 5" Boot Kits

LMR Cables

Part #	Cable Size & Type	Holes Size	# of Holes	U of M
BBLR24	LMR-240	0.240"	4	Each
BBLX4	LMR-400, 3/8" Flex, & RG11U	0.405"	1	Each
BBLR42	LMR-400, 3/8" Flex, & RG11U	0.405"	2	Each
BBLR44	LMR-400, 3/8" Flex, & RG11U	0.405"	4	Each
BBLR9	LMR-900	0.870"	1	Each
BBLR94	LMR-900	0.870"	4	Each

Elliptical Waveguide

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
BBEW43	EW43	2.85" x 1.64"	1	Each
BBEW52	EW52, EWP52, & WE61	2.25" x 1.30"	1	Each
BBEW60	WE60	2.10" x 1.15"	1	Each
BBEW63	EW63, EWP63, & WE65	2.01" x 1.165"	1	Each
BBEW632	EW63, EWP63, & WE65	2.01" x 1.165"	2	Each
BBEW64	EW64, EWP64, & WE70	1.92" x 1.12"	1	Each
BBEW77	EW77 & EWP77	1.76" x 1.04"	1	Each
BBEW85	EW85 & WE108	1.33" x 0.92"	1	Each
BBEW90	EW90 & EWP90	1.32" x 0.80"	1	Each
BBEW903	EW90 & EWP90	1.32" x 0.80"	3	Each
BBEW180	EW180, EWP180, WE190, & WE191	0.80" x 0.49"	1	Each

Rectangular Waveguide

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
BBWR75	WR75	0.85" x 0.475"	1	Each
BBWR90F	WR90 Flex	1.21" x 0.67"	1	Each
BBWR137	WR137	1.50" x 0.75"	1	Each
BBWR137F	WR137 Flex	1.77" x 1.01"	1	Each

Conduit

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
BB34	3/4" Conduit	0.77"	1	Each